Catalogue



Battery chargers

Inverter-chargers

Battery monitoring



Engineered power

Inverters

Battery splitters

Battery separators

MPPT solar charge controllers

DC/DC converters

SWISS made power

Summary

The company	3	
Applications	6	
- Applications in remote areas	6	
- Mobile applications	8	
- Backup applications	10	
- Self-consumption systems	12	
Products	14	
- Sine wave inverter-chargers	14	
- Sine wave inverters	24	
- MPPT solar charge controller	26	
- Battery chargers	28	
- DC/DC converters	29	
- Battery splitters	30	
- Battery separators	30	
- Battery protection	31	
- Battery monitoring	31	
Appendices	32	
- Technical data	32	
- How to find us	40	

Photos credits

Robert Hofer, Céline Ribordy: Studer's products; Hacksss-Fotolia.com: p. 10; Getek AS: p. 18; Jeanneau: p. 8 top; Meteorisk: p. 3, 40; Perspective: p. 5, 28; PROSOL: p. 12; Siblik: p. 25; Steca: p. 6 bottom; Studer Innotec Ltd.: p. 15.

Graphism Atelier Perspective, R. Gigon, Sion. October 2012

Studer Innotec was established in 1987, not as a result of market research, but founded on my wish to improve solar systems. Therefore it was natural to focus on the main component of a battery system: the inverter.

Three years later the company was manufacturing its first inverter models, eight years later it started to export them and then gradually opened up to new application areas (mobile applications, backup systems and industrial applications).

Today Studer Innotec provides an extensive product range with over 60 products that assure storage, conversion and management of energy, of which over 95% are exported through our distributor network with over 100 partners worldwide.

The key success factor in maintaining our competitive lead is constant innovation. Through its know-how and experience, Studer Innotec ensures the renewal of its product range as well as expanding into new applications such as self-consumption systems and mini-grids.

Our company's vision is the same as at its beginnings: more than a product, we offer innovative solutions to optimize any solar system whatever the application. These solutions are designed and manu-





Uompany



Production Integration and Flexibility

The company's philosophy has always been to master the complete process: from development to product sales. This is why Studer Innotec Ltd., since its beginning, is a company vertically integrated; therefore, capable of far greater flexibility than its competitors.

In other respects, to turn the markets expectations into products and services, a 10 people team is fully dedicated to Research & Development.

The Performance Choice

Studer Innotec's high-tech concept of its products as well as the performance and reliability selection, drive the company to choose its components with the greatest care. This is the reason why the Studer Innotec Ltd. has selected the latest technologies; such as digital signal processors (DSP) that provide higher efficiency to its inverters.

町田原

Ease in Use and Product Versatility

Quality choice will continue to guide Studer Innotec's strategic axis towards the future. Beyond performances, the next inverters will have increased ease in use and will offer greater versatility to the users.

Proximity with Clients

From research to industrialization, Studer Innotec Ltd. endeavors to carry on its human and financial investments in order to keep its lead in terms of global offer and proximity with clients. This closeness is maintained by a network of qualified service partners. Partner addresses can be found on the company website, under « Distributors ».



Company



A complete solar system

Applications in remote areas



Security and comfort (lighting, heating, household appliances, leisure electronics, telecoms...) can now be provided by autonomous energy systems; when far away from any electrical grid, either by choice or reason.

These systems consist firstly of an energy source; normally a genset, a solar generator, a wind turbine or a combination of these;



secondly of a battery storage, and then thirdly of devices (inverter-charger, battery charger) able to charge the battery from this energy source and to supply users with AC voltage (inverter, inverter-charger).

The examples below show the products in some stand-alone applications.

Village electrification





A complete solar system can be built by combining an inverter from the AJ series and the «solar charge control» integrated function (as an option). One single device can then both supply alternating current (AC) and charge the battery with direct current (DC).

Quality AC voltage for all electrical appliances





The inverter supplies, exclusively from a battery, any kind of appliance using AC voltage, without exception. It converts the battery's DC voltage into AC voltage at a higher quality than what is available from the public grid. The MPPT solar charge controller optimally charges the battery from the solar generator.

Inverters

AJ series p. 24 (275 - 2'400VA)

Inverters

Xtender series p. 14 (900 - 72'000VA)

(1′400 - 4′000VA)	p. 22
AJ series	p. 24

p. 24 (275 - 2'400VA)

MPPT solar charge controller

VarioTrack series p. 26 (65 - 80A)

3-phase grid 3 x 400Vac for high power appliances



STUDER

6

Applications



This hybrid system provides great flexibility in supply and increased autonomy in relation to each energy source. The appliances AC voltage supply is done directly from the energy source through the transfer relay, or from the battery through the inverter function. The charger function allows battery charging with the genset. The genset's size can be reduced thanks to the Smart-Boost function.

(Application Note AN007/www.studer-innotec.com)

Inverters

Xtender series p. 14 (900 - 72'000VA)

Compact series p. 22 (1'400 - 4'000VA)

MPPT solar charge controller VarioTrack series p. 26 (65 - 80A)

A 3 x 400Vac 3-phase grid can be built with 3 inverters for supplying high power appliances. In case of an increased power requirement, it is possible to set up to 3 inverters in parallel Inverters

Xtender series p. 14 (900 - 72'000VA)

MPPT solar charge controller VarioTrack series p. 26 (65 - 80A)



Mobile applications



A simple on-board energy system is often necessary to power the AC voltage appliances, while the vehicle or the boat is away from the electrical grid (port, garage, camping...).

In this case, energy is stored in the battery, which is actually charged by power sources on-board, such as a genset, solar generator, wind turbine, alternator or a combination of these. Studer Innotec offers the product range that secures the management and conversion of



this energy, while securing an optimal power supply to the on-board appliances.

The examples below show our products in some mobile applications.

3 x 400Vac 3-phase grid on-board





A simple and reliable on-board system



An upgradeable power



Inverters

Xtender series p. 14 (900 - 72'000VA)

STUDER

Compact series p. 22 (1'400 - 4'000VA)

In this system, a battery separator enables one or several auxiliary batteries to be charged, once the primary battery is charged.



8





bles the creation of a 3-phase grid and to simultaneously charge the battery, even if only a single phase is available as a power source.

Inverters **Xtender series** p. 14 (900 - 72'000VA)

The source being a variable power alternator, the Smart-boost will supply the power difference in order that the power delivered is always the same (Application Note AN004/ www.studer-innotec.com).

Inverters **Xtender series** p. 14 (900 - 72'000VA)







Appliances such as fridges, PCs, emergency lights, etc. which are supplied by the public grid and cannot afford any power cut, are electrically secured.

An inverter-charger with transfer relay or a combination of an inverter and a charger guarantees that the battery is well maintained and that an uninterrupted power supply to strategic appliances is sustained.

Studer Innotec Ltd. offers solutions from 275VA up to 72kVA with a one of a kind product choice that remains unchallenged on the market.







Solsafe - a backup system for grid connected solar installations



Uninterruptible power supply on-line



In this system, the battery charge functions and appliances' power supply are separated : On one side is a battery charger, and on the other, an inverter. Grid current fluctuations have no impact on the appliances.

10



Inverters

AJ series p. 24 (275 - 2'400VA)

Battery chargers MBC series p. 28







In this configuration the grid supplies directly to the appliances, thanks to the inverter-charger's by-pass function. In case of a power drop or cut in the grid, the inverter-charger Inverters **Xtender series** p. 14 (900 - 72'000VA)

Compact series p. 22 (1'400 - 4'000VA)

An inverter-charger is used there to provide a backup power in case of public grid outage. As soon as the power shuts off the inverter-charger switches on inverter mode and assures an uninterruptible power supply.

Inverters **Xtender series** p. 14 (900 - 72'000VA)

Compact series p. 22 (1'400 - 4'000VA)





Self-consumption systems

Optimising self-consumption with partial backup

In order to give priority to consumption of the energy generated from your own solar- or renewable installation, different systems including the Xtender inverter-chargers can be set up.



These systems store excess energy produced during daytime in batteries to be used at a later time, maximizing the self-consumption. The public grid will only be used to import or to export small amounts of energy if absolutely necessary.

Priority to renewable energy without grid-injection



When it is forbidden or there is no incentive to inject energy into the public grid, an Xtender inverter-charger combined with a VarioTrack MPPT solar charge controller will minimize the grid consumption in favour of the locally produced energy. They will also guarantee an energy supply in case of grid-failure. This solution is easy to set-up using Studer products.





Inverters

Xtender series p. 14 (900 - 72'000VA)

STUDER

MPPT solar charge controller

VarioTrack

series p. 26 (65 - 80A)

This system will secure all users (household) however appliances it requires that the power of the Xtender is at least equivalent to the grid inverter and that it covers the household's power needs. The self-consumption is optimized by means of an expert system (SCADA) supplied by partners of Studer Innotec. A correctly sized system adapted to meet the customer's needs guarantees the energy supply during power outages of the public grid, even for longer periods.



Inverters **Xtender series** p. 14 (900 - 72'000VA)





Xtender XT5 XTS 900-12 XTS 1200-24 XTS 1400-48

Xtender **XTM**

XTM 1500-12 XTM 2000-12 XTM 2400-24 XTM 2600-48 XTM 3500-24 XTM 4000-48



IP54

20

XTH XTH 3000-12 XTH 5000-24 XTH 6000-48 XTH 8000-48

Xtender



The Xtender series offer an optimal use of all sources that can be found in hybrid systems, whatever their connecting mode (AC or DC bus), up to the nominal power of the Xtender system (single, parallel and/or threephase).

Sine wave inverter-chargers

Xtender Series

The Xtender series provides unmatched freedom of use due to its many functions. In a basic application, it offers a total package: the functions of inverter, battery charger, transfer system and assistance to the source. These functions can be combined and controlled in a totally automatic way for exceptional ease and optimal management of available energy.

The Xtender is equipped with a command entry and 2 configurable auxiliary contacts. This allows an automatic control of the genset or a loadshedding when the battery voltage is too low. The flexibility then obtained makes it possible

to implement special functionnalities, often necessary for a good energy management in standalone systems.

Features and performances

- Outstanding efficiency and overload. •
- Perfect management and limitation of AC sources.
- Power shaving of the consumption peaks.
- Automatic allocation of the power available. •
- Active filtering of the load steps on the genset. •
- Automatic protection of the sources against overload. •
- Battery priority (or to renewable sources).
- Parallel and three-phase setting, up to 9 units (72kVA). •
- Powerful multi-stage PFC charger. •
- Ultra-short transfer time (from 0 to 15ms max.).
- Automatic and efficient stand-by.
- 2 programmable auxiliary contacts (optional on the XTS).
- Compatible with AC coupling.
- XTS electronically protected against reverse polarity.
- Display, programming and data logging integrated in the remote control RCC.
- Interactive with the Battery Status Processor (BSP).
- RS-232 communication for remote supervision.



Xtender range	Battery voltage	AC voltage	Output power P30/Pnom	Power Smart- Boost	Charge current	Transfer current
XTS 900-12	12V	230Vac*	900VA** / 500VA	900VA**	0 - 35A	16A
XTS 1200-24	24V	230Vac*	1200VA** / 650VA	1200VA**	0 - 25A	16A
XTS 1400-48	48V	230Vac*	1400VA** / 750VA	1400VA**	0 - 12A	16A
XTM 1500-12	12V	230Vac*	1500VA / 1500VA	1500VA	0 - 70A	50A
XTM 2000-12	12V	230Vac*	2000VA / 2000VA	2000VA	0 - 100A	50A
XTM 2400-24	24V	230Vac*	2400VA / 2000VA	2400VA	0 - 55A	50A
XTM 2600-48	48V	230Vac*	2600VA / 2000VA	2600VA	0 - 30A	50A
XTM 3500-24	24V	230Vac*	3500VA / 3000VA	3500VA	0 - 90A	50A
XTM 4000-48	48V	230Vac*	4000VA / 3500VA	4000VA	0 - 50A	50A
XTH 3000-12	12V	230Vac*	3000VA / 2500VA	3000VA	0 - 160A	50A
XTH 5000-24	24V	230Vac*	5000VA / 4500VA	5000VA	0 - 140A	50A
XTH 6000-48	48V	230Vac*	6000VA / 5000VA	6000VA	0 - 100A	50A
XTH 8000-48	48V	230Vac	8000VA / 7000VA	8000VA	0 - 120A	50A

* For the 120Vac/60Hz version, -01 is added to the model designation. ** These features are valid only when using the cooling module ECF-01. Complete technical specifications on page 32.

Function Smart-Boost and active filtering

With this function it is possible to interact directly with the AC source (Genset or grid) and to implement some basic functions such as:

- Efficient and immediate limitation of the current of the source, including fore non linear or inductive/ capacitive loads, protecting efficiently the breakers during connection to shore power or to a camping power counter with limited current (function of power shaving and of power assistance) (more information on our website and in the Application Note AN001/www.studer-innotec.com).
- Power shaving of load steps on the generator allowing therefore an optimal sizing of the generator and asssuring the best possible efficiency of the fossile fuels (function of filtering and of power assistance).

The function of assistance to the source enables also to implement advanced functions such as the priority use of renewable energy, even when the grid is available (more information on our website and in the Application Note AN002/www.studer-innotec.com).



14

Products





Sine wave inverter-chargers







Remote control and programming centre RCC-02 or RCC-03

Apart from the enclosure difference, adapted for wall or panel mounting, both units have exactly the same features and allow the user to survey his system and fully customize it to his needs. RCC gives a controlled access to the many adjustable parameters of the Xtender. It enables the setting of the charge curve of the battery, the programming of the auxiliary contacts and gives access to a lot of operation options. Thanks to its graphic display RCC provides clear and comprehensive indications on the state of the system in selectable language. The unit memorizes and displays the events that occurred on an installation and so it does anticipate the problems that might appear. A slot for a SD card is available and it allow the parameters record and download as well as the full software update.



Data logging and analysis

Analyze easily your data with the RCC-02/03 Data logger function that will record on the SD card the main electrical values of your Xtender system during its operation.

These standards enable the follow up on the system's energy consumption evolution, to check the power cuts, the state of the auxiliary contacts, the input currents and voltages, etc.

Studer Innotec Ltd. offers for free two graphical and analysis tools, Xtender Data Analysis Tool and Xtender Matlab® Data Analysis (more information on our website and in the Application Note AN006/www.studer-innotec.com).

Battery Status Processor BSP for XTENDER systems

One of the most important information for a safe and effective operating of an energy system with batteries is their state of charge. The BSP offers, for Xtender systems, a highly precise measuring and an extremely efficient algorithm that calculates the state of charge in the most accurate way.

The remote control RCC-02/03 provides the display, the data logging, the graphical display of the state of charge history and the settings. Values of the BSP can be used in the programming of the Xtender system. Besides, 17 different values can be displayed like for instance:

- State of charge
- Voltage (12-24-48Vdc)
- Current
- Time to go
- Throughput energy
- Battery temperature

The 2 models BSP 500 and BSP 1200 are supplied respectively with a shunt 500/1200A and 2 m cable for battery connection, as well as with 5 m communication cable.



Accessories

RCC-02/-03

The remote control module (with 2m eters as well as the display of the value is possible to log the system data, to system. This module is available eithe for panel mounting (model RCC-03).



BTS-01

Battery temperature sensor (with 5 m tion of the adjustable thresholds of the







Module for rail DIN mounting (with 5 m and to the command entry with the mod

BSP 500/1200

Module meant for the measuring and cal 5 m cable). This module is connected to the It allows the display and the datalogging opposite screens) and also the control of

Xcom-232i



Communication module with RS-232 cess to the parameters and measured the link between an Xtender system a system (not supplied).

Xcom-MS





ARM-02 This module only meant for the XTS equipped with 2 auxiliary contacts co. This function is already integrated in



External cooling module (IP54) for mo increase the power of the XTS. The E XTS casing and its mounting can be



X-Connect Mounting frame for multi-XTH system, with DC breakers and fuses, and with r devices upstream and downstream (see



CAB-RJ45-8-xx Communication cable for the connect accessories. The cables are available or 50 m (xx stands for the length). For requires 2 cables of 2 m. One cable is a longer cable can be ordered when n

16

	XT5	хтм	хтн
cable) enables the setting of the param- ues measured. By means of a SD card it save and restore the parameters of the er for wall mounting (model RCC-02), or	•	•	•
cable) offering the automatic compensa- e battery voltage.	•	•	•
cable) giving access to the main ON/OFF dels XTS and XTM.	•	•	
culating of the battery state of charge (with he communication bus of the Xtender. of the values measured and calculated (see the 2 auxiliary contacts of the Xtender.	•	•	•
port and 2 m RJ45 cable, allowing ac- d values of the Xtender system. It makes and a SCADA supervision or control	•	•	•
an Xtender system and one or several e). With this module it is possible to so to the values measured in the solar e charging profile of the battery. SD card of the module RCC or are acces- n module Xcom-232i.	•	•	•
models and for rail DIN mounting, is ontrolled by the XTS. the models XTM and XTH.	•		
odels XTS. The use of this accessory will CF-01 is directly installed on top of the done at any time after installation.	•		
, supplied as a kit. The frame is equipped rail DIN for the mounting of protection re p. 20).			•
tion between Xtenders and to all external in the following lengthes: 2, 5, 10, 20 r instance: one system with 3 Xtenders supplied with every accessory. However necessary.	•	•	•

Products





Sine wave inverter-chargers

The main configurations offered by the Xtender series

Wide modularity

By the implementation of several units, it is possible to create a 3-phase source or to set them in parallel to increase the power available without extra cost. Up to 9 inverters of the Xtender serie shall therefore be combined together up to 72kVA !



Easy set up of multi-units

Xtenders in the heart of the Spitzbergen...



Compatible with standard cable channel (230 x 60 mm)



Inverter, charger and transfer relay

The Xtender basically works as an inverter and as a charger, combined with a transfer relay.

2 or 3 units in parallel on 1 phase

Increase of the power on one phase by setting 2 or 3 Xtender in parallel.

1 phase in and 3 phase out Three-phase power supply from a single phase source.

3 phase in and 3 phase out Three-phase source for a three-phase power supply.

3 phase + with one reinforced phase

Three-phase power supply with increase of the power on one phase by setting 2 or 3 Xtender in parallel on this phase.

3 Xtender in parallel on 3 phases

Three-phase power supply with 3 Xtender on each phase, for power up to 72kVA.

STUDER/ 18

Products

















Sine wave inverter-chargers

X-Connect system



Offers a flexible and cost effective solution for high power systems based on the XTH inverter.



Centralized



Parallell





Parallell + 3-phase







Frame is supplied with:

- 1 Pre-installed DC circuit breakers
- (2) Pre-installed DC fuses
- (3) Pre-installed DIN rails
- 4 Interconnection pipes and gland for auxiliary contact wiring
- (5) Interconnection pipes and gland for AC wiring
- 6 Interconnection pipes and gland + 90 mm² wire terminated with appropriates ring tongues for DC wiring from Xtender to breakers and fuses

Screws set for frame assembly



Solsafe: the anti-blackout system for grid connected solar installations

Despite a solar system on your house, in case of power outage, the grid inverters will shut off and the solar generator, whatever its size, will be useless. Studer Innotec Ldt has developped, already in 2004, a concept in which its inverter-chargers allow to keep energy available from the solar generator, even in case of a power cut.

Compared to other similar solutions, it offers:

Solsafe

Solsafe

S-Box

S-Box: a genuine cabling solution to implement the Solsafe

- Hassle free cabling
- Quick installation
- Easy commissioning

- Sol - So - So - So For Sc dispos



20 STUDER



- Great system flexibility by choosing both the grid inverter power (matching the solar generator) and the stand-alone power (matching the needs for autonomous energy) independently, as long as the stand-alone inverter is as big as, or bigger than the grid inverter.
- The choice of the grid inverter allows working with standard well known products.
- To choose the grid inverter with any voltage input range, independently from the battery voltage.
- A possible and easy upgrade of existing grid-connected solar installations.

The S-Box can be supplied in 4 versions:

For single phase application:

Isafe box 25A for Compact	S-Box-25C
Isafe box 25A for Xtender	S-Box-25X
Isafe box 25A for Compact with ENS-26	S-Box-25C-E
Isafe box 25A for Xtender with ENS-26	S-Box-25X-E
olsafe implementation in 3ph systems, a sche	matic is at
al on simple request.	

Solsafe – a backup system for grid connected solar installations The installation of our solution Solsafe in a grid connected solar system enables to secured totally or partially the power supply in case of a power cut, and so to keep on using the solar energy being produced (Application Note AN003/ www.studer-innotec.com).





XP COMPACT

XPC 1400-12

XPC 2200-24

XPC 2200-48

COMPACT

C 1600-12

C 2600-24

C 4000-48

Sine wave inverter-chargers

Compact series

The Compact series models consist of 3 fully automatic functions: a sine wave inverter, a battery charger and a transfer system. Equipped with highend technology, they optimally perform, thanks to Studer Innotec's extensive experience in the field of electrical supply.

Features and performances

- True sine wave voltage.
- Suitable for any kind of electrical appliance.
- Reliable and silent working with all kind of loads.
- Outstanding overload capabilities.
- Stand-by level adjustable over a large range and from a very low threshold.
- 4 STEP battery charger with PFC.
- Ultra-fast transfer relay.
- High efficiency. •
- Full internal protection.
- Ultra-fast regulation.
- Microprocessor controlled.

Norm E certification

The XPC 1400-12, XPC 2200-24, C 1600-12 and C 2600-24 are certified to the ECE-R 10 norm.

Compact range	Output power P30/Pnom	Battery voltage	AC voltage	Charge current	Transfer current	Solar option (-S)
XPC 1400-12	1400VA / 1100VA	12Vdc	230Vac*	0 - 45A	16A	30A
XPC 2200-24	2200VA / 1600VA	24Vdc	230Vac*	0 - 37A	16A	30A
XPC 2200-48	2200VA / 1600VA	48Vdc	230Vac*	0 - 20A	16A	20A
C 1600-12	1600VA / 1300VA	12Vdc	230Vac	0 - 55A	16A	30A
C 2600-24	2600VA / 2300VA	24Vdc	230Vac	0 - 55A	16A	30A
C 4000-48	4000VA / 3500VA	48Vdc	230Vac	0 - 50A	16A	20A

* For the 120Vac/60Hz version, -01 is added to the model designation. Complete technical specifications on page 33.

Multifunctional contact

The 16 A. potential free contact can be programmed according to the user wishes. It reacts according to battery levels, as well as to the system status (alarm conditions, public grid presence, sunlight's presence...), and provides:

1/ Automatic disconnection of second priority users (conditional supply).



- 2/ Alarm signalization, acoustic signal, MODEM, radio alarm etc.
- 3/ Conditional battery charge.

Accessories



RCC-01 Remote control State of the system displayed by LED plied with a 20 m cable). *compulsory for the programming of

CT-35 Temperature sensor This sensor adapts charge levels to th (supplied with 3 m cable).



ARM-01 Auxiliary relay module Equipped with 3 programmed relays inverter-charger's auxiliary contact, th tem to be implemented (see page 11).



CFC-01 Cover

This cover provides additional connect glands.



C-IP22 Cover

Cover for a protection against intrusion mounting of the device. It extends the pacts and Compacts from IP 20 to IP 22

Optional built-in solar charge controller (-S) The XP Compact and Compact models

are available with an optional built-in PWM charge controller (I/U/Uo); making the inverter-charger an « all in one » device for a solar installation.

STUDER 22

.....



	XP COMPACT	COMPACT
and remote programming* (sup- the XP Compacts	•	•
ne battery's temperature variations	•	•
and a fourth one which is like the his module allows the Solsafe sys-	•	•
ction protection by means of	•	•
ns or projections, installed after the protection index of the XP Com- 2.	•	•







AJ AJ 275-12 AJ 350-24 AJ 400-48

AJ AJ 500-12 AJ 600-24 AJ 700-48



AJ 1000-12 AJ 1300-24

AJ AJ 2100-12 AJ 2400-24



AC Solar Output power Battery AJ range voltage option (-S) P30/Pnom voltage AJ 275-12 (-5) 275 VA / 200 VA 12 Vdc 230 Vac* 10 A 350 VA / 300 VA 24 Vdc 230 Vac* AJ 350-24 (-5) 10 A AJ 400-48 (-5) 400 VA / 300 VA 48 Vdc 230 Vac* 10 A AJ 500-12 (-5) 500 VA / 400 VA 12 Vdc 230 Vac* 15 A AJ 600-24 (-5) 600 VA / 500 VA 24 Vdc 230 Vac* 15 A AJ 700-48 (-5) 700 VA / 500 VA 48 Vdc 230 Vac* 15 A AJ 1000-12 (-5) 1000 VA / 800 VA 12 Vdc 230 Vac* 25 A AJ 1300-24 (-5) 1300 VA / 1000 VA 24 Vdc 230 Vac* 25 A AJ 2100-12 (-5) 2100 VA / 2000 VA 12 Vdc 230 Vac* 30 A 2400 VA / 2000 VA 24 Vdc 230 Vac* AJ 2400-24 (-5) 30 A

> * For the 120Vac/60HZ version, -01 is added to the model designation. Complete technical specifications on pages 34-35.

Sine wave inverters

AJ series

The AJ range consists of sine wave inverters that convert a battery's DC voltage into AC voltage, which can be used by all electrical appliances.

Features and performances

- High and steady efficiency.
- Outstanding overload capabilities.
- Digital regulation and control by microprocessor.
- Electrical supply to any type of appliance.
- Full internal protection.
- Battery lifetime optimization (B.L.O.) function.

Norm E certification

Supplied with battery and AC cables.

The AJs in 12 and 24Vdc are certified to the ECE-R 10 norm.

Battery Lifetime Optimization: B.L.O.

With this function the AJ inverters offer an advanced protection of the battery, by a smart management of the low voltage disconnection (LVD).



Accessoire



JT8 Remote control Enables the control (ON/OFF) and the remote display (ON / Standby / Temporary off). (supplied with a 5 m cable)

Option plug for remote control RCM

Connection (plugs male and female) to start/stop an inverter AJ under certain circumstances:

- RCM 01: ON when a contact is closed.
- RCM 02 : ON when a voltage is present on the plug.
- RCM 03: ON when a contact is open.

For the AJ inverters 275 to 700VA. Supplied with a «connector Jack» 3.5 mm.



Rural electrification (Solar Home System)

The rural electrification and the inverters of the AJ series: excellence to the benefit of the development of remore areas and populations. Choosing AC voltage for the rural electrification systems is going for

simplicity, reliability and cost saving. Indeed, compared with a DC voltage one, a system with an inverter is often more efficient from 100W of solar power.

The AJ series, due to its overload capability and to its very reliable stand-by system adjustable from 2W, is the most suitable range of inverters to meet the rural electrification technical and economical requirements.



STUDER 24



AJ 1000-12, AJ 1300-24 AJ 2100-12, AJ 2400-24



Option built-in solar charge controller

For a complete solar system!

The models AJ can be supplied equipped with an optional integrated PWM solar charge controller, making the inverter an «all in one» device for a solar installation.





VT-80

VarioTrack series

The VarioTrack solar charge controller maximizes the energy generated from solar panels in any solar installation. It contains a MPPT (Maximum Power Point Tracking) algorithm that continuously tracks the maximum power point and automatically charges the batteries in an optimal way with all the available solar power.

Features and performances

against incorrect wiring

The VarioTrack in an Xtender system

Designed to function in any solar installation, the VarioTrack is working optimally in an Xtender system. The communication between the two devices allows in particular for a synchronized battery management.

VarioTrack VT-65





Rugged and durable, this device is designed to
perform in harsh environmental conditions (IP54)
High conversion efficiency, 98%

Easy and safe commissioning with full protection

- Up to 15 VarioTrack in parallel on the same communication bus
- 4 step charger for longer battery life
- Low self-consumption: <1W in night time mode
- Display with 7 LEDs showing status and current
- Comprehensive display, programming and datalogging with RCC-02/-03
- Suitable for any solar system
- Optimal usage in an Xtender system with a synchronized battery management



VarioTrack range	Max. Recom. power of the solar generator	Maximum power of the solar generator	Maximum battery charging current	Maximum charging current to the battery
	12 V	1000 W	80 Vdc	
VT-65	24 V	2000 W	150 Vdc	65A
	48 V	4000 W	150 Vdc	
	12 V	1250 W	80Vdc	
VT-80	24 V	2500 W	150 Vdc	80A
	48 V	5000 W	150 Vdc	

* Complete technical specifications on pages 36.

Psol 1462 l 111 Udc Upu 55.8 Ide Ibat lhat 2 Ude





Display and programming possibilities

The VarioTrack is fitted with several indicator lights and a control button for its basic operation. It is also possible to do basic programming using the DIP switches situated inside the device. By adding a remote control and programming center RCC-02/-03, the VarioTrack can use all functions available in the remote control such as display, programming, data logging etc.

Accessories



RCC-02/-03 Remote control and progr The remote control module (with 2m parameters as well as the display of the a SD card it is possible to log the syst parameters of the system. This module is available either for wa panel mounting (model RCC-03).



BTS-01 Battery temperature sensor Battery temperature sensor (with 5 m compensation of the adjustable thresh

26



	VT-65	VT-80
ramming centre cable) enables the setting of the he values measured. By means of tem data, to save and restore the Il mounting (model RCC-02), or for	•	•
cable) offering the automatic holds of the battery voltage.	•	•

Battery chargers

MBC series

The MBC chargers enable battery charging from an AC voltage supply source (genset, public grid, shorepower, etc.). These chargers are also watertight and therefore especially designed for outdoor applications (IP 65).

Features and performances

- Universal input voltage.
- Charge of lead acid batteries with liquid or gelled (GEL) electrolyte.
- Protection against battery overcharge.



MBC range	Battery voltage	Input voltage	Output current	Output
MBC 12-06/1	12 Vdc	230 Vac ±15%	6 A	1
MBC 12-15/1	12 Vdc	230 Vac ±15%	15 A	1
MBC 24-03/1	24 Vdc	230 Vac ±15%	3 A	1
MBC 24-08/1	24 Vdc	230 Vac ±15%	8 A	1
MBC 24-32/1	24 Vdc	230 Vac ±15%	32 A	1

Complete technical specifications on page 37.



DC/DC converters

/////////

MDCI and MDC series

	MDCI range	Power	Output Current	Input variant	Output variant	lsolated
	MDCI 100	100 W	8/4 A	A/B/C/D	12.5 or 24 Vdc	Yes
	MDCI 200	200 W	16.5/8 A	A/B/C/D	12.5 or 24 Vdc	Yes
	MDCI 360	360 W	30/15 A	A/B/C/D	12.5 or 24 Vdc	Yes
MDCI 360 A24 Charger		330 W	30/15 A	А	24 Vdc	Yes
	A = 9-18 Vdc B	= 20-35 Vdc	C = 30-60 Vdc	D = 60-120 Vdc	(ex. MI	DCI 200 D24)

MDC range	Power	Output Current	Input voltage	Output voltage	lsolated
MDC 1224-7	170 W	7 A	9-18 Vdc	24 Vdc	No
MDC 2412-5	65 W	5 A	18-35 Vdc	13.2 Vdc	No
MDC 2412-8	105 W	8 A	18-35 Vdc	13.2 Vdc	No
MDC 2412-12	160 W	12 A	20-35 Vdc	13.2 Vdc	No
MDC 2412-20	275 W	20 A	20-35 Vdc	13.8 Vdc	No
MDC 2412-30	415 W	30 A	20-35 Vdc	13.8 Vdc	No

The MDC 2412-20 and 2412-30, as well as the MDCI 360 A24 «Charger» can also be used to charge a battery.

The DC/DC converters type MDCI and MDC are used, depending on the model, either to step up or to step down a DC voltage.

The MDCI range converters are electrically isolated.

Features and performances

- High efficiency.
- Low consumption.
- Protection against short-circuit, overheat, overvoltage and reverse polarity.
- Great stability of the output voltage for a more reliable system.



Complete technical specifications on page 37.



MOSFET battery splitters

MBI series

The MBI MOSFET battery splitters generate an insignificant voltage drop. They supply the charger's or alternator's current to several batteries. All batteries are thus charged at the same time, and therefore will not charge or discharge each other.

VIBI range	Input	Charge current	Charge input	Outputs
MBI 100/2	12/24 Vdc	100 A	1	2
MBI 150/2	12/24 Vdc	150 A	1	2
MBI 100/3	12/24 Vdc	100 A	1	3
MBI 150/3	12/24 Vdc	150 A	1	3
MBI 200/3	12/24 Vdc	200 A	1	3
MBI 2-100/3	12/24 Vdc	100 A	2	3

Features and performances

- Automatic adjustment to the batteries voltage.
- Possible charge of the battery from an alternator
- Voltage drop < 0.4 V at 100 Amp.
- Suitable for electronic alternators.

Features and performances

Protects the auxiliary battery from any

Insignificant voltage drop.

overvoltage.

Complete technical specifications on page 38.

Batteries separators

<u>ل</u>لک

MBR series

The MBR batteries separators allow to supply the auxiliary battery or the appliances, as soon as the mainbattery voltage is high enough.

MBR range	Battery voltage	Charge current	Batteries	
MBR 12/24-100	12/24 Vdc	100 A	2	
MBR 12/24-160	12/24 Vdc	160 A	2	
MBR 12/24-500	12/24 Vdc	500 A	2	

Complete technical specifications on page 38.









Optional accessories

- 2 fuseholders.
- and software.
- Communication kit, type SBM-COM-USB, including USB interface box, 1.8 m of USB cable and software.
- Temperature kit, type SBM-TEMP-20, with a temperature sensor and 20 m cable.
- Shunt 1200 A / 50 mV, type SH-1200-50, for battery monitoring in large system.

STUDER



The SBM-02 is a highly accurate battery monitor with a history data memory. It is supplied together with a 500A/50mV shunt. This device is designed for 12 and 24V batteries. The optional SBM-PS-02 voltage pre-scaler extends the use of the SBM-01 to 27-175V batteries.

Features and performances

- Digital display of the 6 most important parameters of a DC power system:
 - 1. Battery voltage (V)
 - 2. Current (A)
 - 3. Consumed Ampere-hours (Ah)
 - 4. Sate-of-charge (%)
 - 5. Time-to-go (h:m)
 - 6. Temperature (°C or °F)

• Connection kit, type SBM-CAB-20, including 20 m of twisted pair cable (3 x 2 x 0.5 mm²) and

• Communication kit, type SBM-COM, including RS232 interface box, 1.8 m of 9p DSUB serial cable



12Vdc

9.5 - 17Vdc

93%

2000VA

4.8kVA

100A

1500VA

1500VA

3.4kVA

70A



Nominal battery voltage

Continuous power @ 25°C

Maximum asymmetric load

Consumption OFF/Stand-by/ON

Overload and short-circuit protection

Load detection (stand-by)

Maximum efficiency

Output voltage

Output frequency

Harmonic distortion

Overheat protection Battery charger

Charge Characteristic

General data

Input voltage range

Output current max. Transfer time Multifunction contacts

Dimension hxwxl [mm]

Operating temperature range Relative humidity in operation

Remote control RCC-02 or RCC-03

Remote Control Module RCM-10 (3 m)

2 aux. contacts module ARM-02

Battery temp. sensor BTS-01 (3 m)

Communication cable for 3ph and // CAB-RJ45-8-2

Protection index

Conformity

Ventilation

Acoustic level Warranty Accessoires

Module XCOM-232i

Bridge XCOM-MS

Cooling Module ECF-01

Input frequency

Weight

Maximum charging current

Temperature compensation

Power Factor Correction (PFC)

Input current max. (transfer relay) /

Power 30 min. @ 25°C

Power 5 sec. @ 25°C

Maximum load

Cos φ

Input voltage range

Model

Inverter



XTS 900-12 XTS 1200-24

650**/500VA 800**/650VA

24Vdc

19 - 34Vdc

1200**/1000VA

2.5kVA

93%

25A

16Aac/20Aac

Module ARM-02 with 2 contacts, in option

9 kg

110x210x310 110x210x310 110x210x310

IP54

100%

Optional cooling module ECF-01

٠

٠

.

•

.

.

•

48Vdc

38 - 68Vdc

900**/750VA

1400**/1200VA

2.8kVA

93%

12A

9.3 kg

٠

٠

.

.

٠

٠

٠

•

12Vdc

9.5 - 17Vdc

900**/700VA

2.3kVA

93%

35A

8.2 kg

٠

٠

٠

٠

٠

٠

٠

.



XTS 1400-48 XTM 1500-12 XTM 2000-12 XTM 2400-24 XTM 2600-48 XTM 3500-24 XTM 4000-48 XTH 3000-12

48Vdc

38 - 68Vdc

2600VA

6.5kVA

96%

6 steps: Bulk-Absorption-Floating-Equalization-reduced floating-periodic absorption

Number of steps, thresholds, end current and times completely adjustable with the RCC-02/-03

30A 90A

With BTS-01 or BSP 500/1200

EN 61000-3-2

150 to 265Vac / 50 to 140Vac (1) 45 to 65Hz

24Vdc

19 - 34Vdc

3000VA

3500VA

9kVA

94%

Up to short-circuit

Up to Pcont.

2 to 25 W

0.1-1

Pure sine wave 230Vac (± 2%) / 120Vac (1)

Adjustable 45 - 60Hz (1) ± 0.05% (crystal controlled)

<2% Automatic disconnection with 3 time restart attempt

Warning before shut-off - with automatic restart

48Vdc

38 - 68Vdc

3500VA

4000VA

10.5kVA

96%

50A

12Vdc

9.5 - 17Vdc

2500VA

3000VA

7.5kVA

93%

160A

.

24Vdc

19 - 34Vdc

2000VA

2400VA

6kVA

94%

55A

XTS 900-12 XTS 1200-24 XTS 1400-48 XTM 1500-12 XTM 2000-12 XTM 2400-24 XTM 2600-48 XTM 3500-24 XTM 4000-48 XTH 3000-12

1.1W/1.4W/7W 1.2W/1.5W/8W 1.3W/1.6W/8W 1.2W/1.4W/8W 1.2W/1.4W/10W 1.4W/1.6W/9W 1.8W/2W/10W 1.4W/1.6W/12W 1.8W/2.1W/14W 1.2W/1.4W/14W



COMPACT series

	XTH 6000-48	XTH 8000-48
L	48\	/dc
	38 - 6	8Vdc
	5000VA	7000VA
	6000VA	8000VA
νA	15kVA	21kVA
%	96	%
1.8W/18W	1.8W/2.2W/22W	1.8W/2.4W/30W
04	100.4	120.4
А	IUUA	120A
0.24	VTU 6000 40	VTU 0000 40
00-24	ATT 0000-40	ΛΙΠ 0000-40
		50Aac/80Aac
ka	42 ka	46 ka
	230x3	0x500
	2007/0	
	•	•
•		•
•	•	
• • •	•	•
•	•	•
•	•	•
• • •	•	•
	•	•
	•	•
	•	•
• • • • • • • • • • • • • • • • • • • •	•	•
• • • • • • • • • • • • • • • • • • • •	•	•

ny sei ings

				50 <i>A</i>	Aac/56Aac				50
				<15 ms					
		2	independent c	ontacts (potent	tial free 3 point	ts, 16Aac/5Adc)			
15 kg	18.5 kg	16.3	2 kg	21.2 kg	22.9 kg	34 kg	40 kg	42 kg	
	133x3	22x466		133x3	22x466	230x300x500	230x300x500	230x3	00x5
					IP20				
Directive EM	C 2004/108/EC Low voltage	EN 61000-6-1, directive 2006/	EN 61000-6-3, 95/EC: EN 6204	EN 55014, EN 40-1-1, EN 5009	55022, EN 610 91-2, EN 60950	00-3-2, 62040-2 -1			
			-2	0 à 55°C					
				95%	6 without cond	lensation			
					Forced from	55°C			
		<4	0dB / <45dB (w	vithout/with ver	ntilation)				
			5	5 years					
•	•	•	•	•	•	•	•	•	
•	•	•	•	•	•	•	•	•	
•	•	•	•	•	•	•	•	•	
•	•	•	•	•	•				
•	•	•	•	•	•	•	•	•	
•	•	•	•	•	•	•	•	•	

* Adjustable with the RCC-02/-03

Mounting frame X-Connect

** These features are valid only when using the cooling module ECF-01.

⁽¹⁾ With -01 at the end of the reference, means 120V/60Hz. Available for all Xtenders except XTH 8000-48

Data may change without any notice.

STUDER/

Appendices





AJ series





Model		AJ 275-12	AJ 350-24	AJ 400-48	AJ 500-12	AJ 600-24	AJ 700-48		
Inverter									
Nominal battery	voltage	12Vdc	24Vdc	48Vdc	12Vdc	24Vdc	48Vdc		
Input voltage ray	200	10.5 – 16Vdc	21 – 32Vdc	42 – 64Vdc	10.5 – 16Vdc	21 –32Vdc	4264Vdc		
input voitage rai	nge	(24Vdc max.)	(44Vdc max.)	(64Vdc max.)	(24Vdc max.)	(44Vdc max.)	(64Vdc max.)		
Continuous pow	ver @ 25°C	200VA	300VA	300VA	400VA	500VA	500VA		
Power 30 min. @	⊉ 25°C	275VA	350VA	400VA	500VA	600VA	700VA		
Power 5 min. @	25°C	350VA	500VA	600VA	575VA	675VA	900VA		
Power 5 sec. @ 2	25°C	450VA	650VA	1000VA	1000VA	1200VA	1400VA		
Maximum asym	metric load	150VA	150VA	200VA	250VA	300VA	300VA		
Max. efficiency ((%)	93%	94%	94%	93%	94%	94%		
Cos φ max.		0.1 – 1 up to 200 VA	0.1 – 1 up to 300 VA	0.1 – 1 up to 300 VA	0.1 – 1 up to 400VA	0.1 – 1 up to 500VA	0.1 – 1 up to 500VA		
Detection of the	load	2W (only with the solar optic	on -S)		Adjustable: 1 → 20W			
Current of short-	-circuit 2 sec. (exit)	2.3A (4.6A*)	3.2A (6.4A*)	4.6 <mark>A</mark> (9.2A*)	5.2A (10.4A*)	5.7A (11.4A*)	7A (14A*)		
Output voltage				Sine wave 230V	ac (120Vac*) ±5%				
Frequency				50Hz (60Hz*) ± 0.05	% (crystal controlled)				
Distortion THD (resistive load)			< 5% (@	Pnom.)				
Consumption St	tand-by	0.3W**	0.5W**	1.1W**	0.4W	0.6W	1.5W		
Consumption «0	ON» no load	2.4W	3.5W	5.2W	4.6W	7.2W	12W		
Overheat protec	tion (±5°C)			Shut down @ 75°C	Auto-restart @ 70°C				
Overload and sh	nort circuit protection	Automatic disconnection with 2 time restart attempt							
Reverse polarity	protection	CO.4	40.4	05.4	100.4		C0.4		
per internal fuse	;	60A	40A	25A	120A	90A	60A		
Deep discharge	battery protection		S	hut off @ 0.87 x Unom -	Auto <mark>m</mark> atic restart @ <mark>U</mark> n	om			
Max. battery vol	ltage		Shi	ut off @ >1.33 x Unom	Autom <mark>a</mark> tic restart @ < U	max			
Acoustic alarm				Before low battery or ov	/erheat <mark>in</mark> g disconnectior	า			
General data									
Weight		2.4 kg	2.6	3 kg		4.5 kg			
Dimensions hxv	vxl [mm]		142x163x84			142x240x84			
Protection index	(IP			IP 30 conform	s to DIN 40050				
Certification ECE	E-R 10 (E24)	•	•	Not available	•	•	Not available		
EC conformity			EN 61	00 <mark>0-6-1, EN 61000-6-3, E</mark>	N 55014, EN 55022, EN 6	60950-1			
Operating tempe	erature	-20°C up to +50°C							
Relative humidit	ty in operation	95% without condensation							
Ventilation force	ed	From 45°C ± 5°C							
Acoustic level		< 45 dB (with ventilation)							
Warranty		5 years							
Approximate co	rrection of Pnom	-1.5%/°C since +25°C							
Recommended	battery capacity			> 5 x Pnom/Unom (rec	ommended value in Ah)				
Length cables (E	Battery/left AC)		1.2m / 1m			1.5m / 1m			
Options		AJ 275-12-S	AJ 350-24-S	AJ 400-48-S	AJ 500-12-S	AJ 600-24-S	AJ 700-48-S		
	Voltage max.	25Vdc	45Vdc	90Vdc	25Vdc	45Vdc	90Vdc		
	Current max.		10Adc			15Adc			
Solar	Principle			Floating 3 st	ages (I/U/UO)				
regulator	Absorption voltage	14.4Vdc	28.8Vdc	57.6Vdc	14.4Vdc	28.8Vdc	57.6Vdc		
	Floating voltage	13.6Vdc	27.2Vdc	54.4Vdc	13.6Vdc	27.2Vdc	54.4Vdc		
Plug for remote	control (RCM)	•	•	•	•	•	•		

......

* 120Vac/60Hz on request

** Standby with solar option -S





Madal		A 1000 12	A I 1200 24	A 2100 12	A 1 2400 24			
Invortor		AJ 1000-12	AJ 1300-24	AJ 2100-12	AJ 2400-24			
Nominal batta	nuvoltaga	12\/da	24\/do	12\/do	24\/do			
Nominal battery voltage		10.5 16V/de (24V/de max)	24Vuc	10 5 16\/dc (20\/dc max.)	24Vuc			
Input voltage range Continuous power @ 25°C		900\/A	21-32 Vdc (44 Vdc max.)	2000\/A	21-32 vuc (40 vuc max.)			
Continuous power @ 25°C		1000\/A	1200\/A	2000VA 2100\/A	2000VA			
Power 30 min. @ 25°C		1000VA	2000\/A	2100VA 2450\/A	2400VA 2800\/A			
Power 5 min. @ 25°C		2200\/A	2000VA	2430VA 5000\/A	5200VA			
Power 5 sec. @ 25°C		500\/A	2000VA	1000\/A	1200\/A			
Max officience		03%	000174	000 VA	94% @ 300\/A			
	y (70)	0.1 – 1 up to 800\/A	0.1 – 1 up to1000\/A	0.1 = 1 μp to 2000\/Δ	0.1 - 1 up to 2000/A			
Dotoction of th	halaad		Adjustable	0.1 − 1 up to 2000/A	0.1 - 1 up to 2000A			
		104 (004 *)			00.4 (00.4 *)			
Current of short-circuit 2 sec. (exit) Output voltage		TUAac (20Aac*)	13Aac (26Aac*)	26Aac (52Aac*)	30Aac (60Aac*)			
	e		Sine wave 230Va	AC (120VAC^) ±5%				
Frequency			50 HZ (60HZ*) ± 0.05	% (crystal controlled)	20/ (@ Da and & Lilia a and)			
Distortion THD (resistive load) Consumption Stand-by		0.714/	< 5% (@ Phom. & Uin nom.)	0.711/	< 3% (@ Phom & Uin hom.)			
Consumption	Stand-by	0.700	1.200	0.700	1.200			
Consumption «ON» no load		ΙΟΨΫ			Ιονν			
Overheat protection (±5°C)		Shut down @ /5°C - Auto-restart @ /0°C						
Snort circuit p	rotection	Durate stard by intermed from 100 A	Automatic disconnection	With 2 time restart attempt	Durate stand by Sinterna of free 150.4			
Reverse polarity protection		Protected by Internal fuse 125A	Shut off @ 0.87 v Lloom - Automatic restart @ Lloom					
Deep discharge battery protection			Shut off @ 0.87 X Unom - 7	Automatic restart @ Unom				
Nax. Dattery v	/oilage		Shut on @ >1.33 X Onorn - A	Automatic restart @ < Omax				
Acoustic alarn	n		Before low dattery or ov	erneating disconnection				
Weight			. ke	10 km	10 km			
Dimonoiono h	www.l.[mm]	0.3) kg	19 Kg	18 Kg			
Differisions ind		IP 20 conform	a to DIN 40050	IP 20 conform	20 to DIN 40050			
Contification E		IF 30 CONION	s to DIN 40050	IF 20 CONIONI				
EC conformitu	, ,	EN 61000.6.1 EN 61000.6.2 EN 55014 EN 55022 EN 60050 1						
Operating top		-20°C up to 150°C						
Delativo humi	iperature	-20°C UP TO +50°C						
Ventilation for		95% Without condensation						
	ceu	From 45°C ± 5°C						
Morronty								
Approvimate	corroction of Pnom	5 years						
Popommondo	d battory capacity		-1.5% CS	mmanded value in Ah)				
Longth cobles	(Rotton/loft AC)	1.5m	> 5 x Filolit/Offolit (reco		o / 1m			
Ontions	(Dattery/left AC)	A I 1000 12 S	A 1 1200 24 S	A 1 2100 12 C	A 1 2400 24 S			
Options	Voltago may	25\/do	45\/do	AJ 2100-12-3	45V/do			
	Current max	23700	43¥00 5Δ	20100	<u>η η σνας</u> ΠΔ			
Solar	Principle	2	Floating 2 of	ر anes (۱/۱ ۱/۱ ۱۸)				
regulator		14 /\/dc	28 8\/de	1/ /\/dc	28 8\/dc			
	Floating voltage	13 6\/dc	20.0 V UC	13 6\/dc	20.0Vdc			
Remote contro	ol IT8 supplied with	13.0900	27.2700	13.0400	27.2900			
5 m cable		•	•	•	•			

* 120Vac/60Hz on request

Data may change without any notice.

STUDER 34







VarioTrack series

Flectrical characteristics PV array side	
Elocitori characteristo i a ditaj sido	
12 V 24 V 48 V 12 V 24 V	48 V
1000 W 2000 W 4000 W 1250 W 2500 W	5000 W
Maximum solar open circuit voltage 80 Vdc 150 Vdc 80 Vdc 1	50 Vdc
Maximum solar functional circuit voltage 75 Vdc 145 Vdc 75 Vdc 1	45 Vdc
Electrical characteristics battery side	
Maximum output current 65 A 80 A	
Nominal battery voltages Automatic / manual set to 12, 24 or 48 Vdc	
Operating voltage range Above battery voltage, minimum 7 V	
Performances of the device	
Power conversion efficiency (in a 48 V typical-system) 98 %	
Maximum stand-by self-consumption (48 V) 25 mA > 1.2 W	
Maximum stand-by self-consumption (24 V) 30 mA > 0.8 W	
Maximum stand-by self-consumption (12 V) 35 mA > 0.5 W	
Charging stages 4 stages : Bulk, Absorption, Float, Equalization	
Battery temperature compensation (available with accessory BTS-01) -3 mV /°C /cell (25°C ref) default value adjustable -8 to 0	mV <mark>/</mark> °C
Electronic protections	
PV reverse polarity Up to -150 Vdc	
Battery reverse polarity Up to -150 Vdc	
Battery overvoltage Up to 150 Vdc	
Over temperature Protected	
Reverse current at night Prevented by relays	
Environment	
Operating ambiant temperature range -20 to 55°C	
Humidity 100 %	
Ingress protection of enclosures IP54, IEC/EN 60529:2001	
Mounting location indoor	
General data	
Warranty 5 years	
Weight 5.2 kg 5.5 kg	
Dimensions h/w/l [mm] 120 / 220 / 310 120 / 220 / 310	50
Parallel operation (separated PV arrays) Up to 15 devices	
Max wire size 35 mm ²	
Glands M 20 × 1,5	
Communication	
Network cabling STUDER communication BUS	
Remote control and display RCC-02/-03 / Xcom-232i	
Menu languages English / French / German / Spanish	
Data logging With RCC-02/03 on SD card · One point every minu	e
Accordance to standards	
CE compliant EMC 2004/108/CE · LV 2006/95/CE · RoHS 2002/95/C	E
Safety IEC/EN 62109–1:2010	
EMC (Electro Magnetic Compatibility) IEC/EN 61000–6–3:2011 · IEC/EN 61000–6–1:2005	

MBC series



Model	MBC 12-06/1	MBC 12-15/1	MBC 24-03/1	MBC 24-08/1	MBC 24-32/1			
Battery voltage (Vdc)	12	12	24	24	24			
Input voltage (Vac)			230 ±15% (40 - 60 Hz)					
Charge voltage (boost) (Vdc)	14.4	14.4	28.8	28.8	28.8			
Charge voltage (float) (Vdc)	13.8	13.8	27.6	27.6	27.2			
Output (A)	6	15	3	8	32			
Cooling		· ·	Heat sink					
Outputs		1						
Efficiency		> 85 %						
Ambient temp. range		-25 to 50°C						
Dimensions Ixwxh (mm)	155x80x36	195x100x47	155x80x36	195x100x46	158x245x47.5			
Weight (kg)	0.9	1.8	0.9	1.8	3.8			
Switch to Floating mode (A)	0.2	0.8	0.2	0.4	3.5			
Secondary fuse (A)	7.5	20	7.5	15	40			
Input wired	•	•	•	•	•			
Ouput wired	•	•	•	•	•			
Warranty			2 years		·			

MDCI and MDC series



MDCI – DC/DC converter, switch-mode, isolated

MDCI 100	MDCI 200	MDCI 360	MDCI 360 Charger		
100	200	360	330		
A-B-C-D	A-B-C-D	A-B-C-D	A		
12.5/8-24/4	12.5/16-24/8	12.5/30-24/15	27.6/12		
8/4	16.5/8	30/15	13		
•	•	•	•		
400					
> 85					
< 25					
-20 / +45°C					
25°C 30°C					
Convection	Convection Fan				
49x88x152	49x88x182	64x1	63x160		
500	600 1400				
	MDCI 100 100 A-B-C-D 12.5/8-24/4 8/4 • 25°C Convection 49x88x152 500	MDCI 100 MDCI 200 100 200 A-B-C-D A-B-C-D 12.5/8-24/4 12.5/16-24/8 8/4 16.5/8 • • • • 200 - 200 - 200 - 200 - 200 - - <t< td=""><td>MDCI 100 MDCI 200 MDCI 360 100 200 360 A-B-C-D A-B-C-D A-B-C-D 12.5/8-24/4 12.5/16-24/8 12.5/30-24/15 8/4 16.5/8 30/15 • • • 200 ×85 201 -20 / +45°C 25°C 25°C 30°C Convection Fan 49x88x152 49x88x182 64x1</td></t<>	MDCI 100 MDCI 200 MDCI 360 100 200 360 A-B-C-D A-B-C-D A-B-C-D 12.5/8-24/4 12.5/16-24/8 12.5/30-24/15 8/4 16.5/8 30/15 • • • 200 ×85 201 -20 / +45°C 25°C 25°C 30°C Convection Fan 49x88x152 49x88x182 64x1		

MDC –DC/DC converter, switch-mode, not-isolated

Model	MDC 1224-7	MDC 2412-5	MDC 2412-8	MDC 2412-12	MDC 2412-20	MDC 2412-30	
Power (W)	170	65	105	160	275	415	
Output current (A)	7	5.5	8	12	20	30	
Input (Vdc)	9-18	18	-35		20-35		
Output (Vdc)	24	13.2			13.8		
Efficiency @ full load (%)	90						
Off-load current (mA)	< 15	< 15 < 5			25		
Operating temperature			-20 / -	+40°C			
Ambiant temp. (20°) increase after 30 min. @ full load	30	30°C		30°C	33°C		
Cooling			Convection			Fan	
Dimensions HxWxD (mm)	49x88x98	49x88x68	49x9	8x88	49x88x126	49x88x151	
Weight (gr)	300	170	250	260	480	600	

Data may change without any notice.

36

Data may change without any notice.

Common features MDCI & MDC				
Paralleling		Max. 2 converters		
Humidity		Max. 95% non condensing		
	Overload	Up to short-circuit		
Protection	Overheating	Output voltage reduction		
	Overvoltage	Transient protection by Varistor		
	Reverse polarity	Fuse		
Casework		Anodized aluminium		
Connections		6.3 mm Faston		
Warranty		2 years		
Norms		EN 50081-1 (emission) EN 50082-1 (immunity) 95/54/EC (automotive directive)		

37

STUDER

Appendices

MBI series



MBI – Battery isolator, voltage drop free

Model	MBI 100/2 IG	MBI 150/2 IG	MBI 100/3 IG	MBI 150/3 IG	MBI 200/3 IG	MBI 2-100/3
Input nominal voltage (Vdc)			12/	24		
Input voltage range (Vdc)			8-(30		
Charge current max. (A)	100	150	100	150	200	100
Input number			1			2
Battery banks		2		;	3	
Voltage drop @ 10a/20A (V)	0.05 / 0.1					
Consumption (mA)			()		
Alternator start	•	•	•	•	•	
Operating temperature (°C)			-40 /	+85		
Dimensions LxHxD (mm)	146x85x92			146x85x152		
Weight (gr)	780	810	780	810	815	780
Nominal voltage 12 or 24V			Automatic	detection		
Insulation to ground			> 500V	@ 60Hz		
Warranty			2 ye	ars		
Norms		EN 5008	1-1 (e <mark>m</mark> ission) EN <mark>50</mark> 082-	1 (immunity) EN 60950-	-1 (sa <mark>fe</mark> ty)	





MBW – Battery watch

Model	MBW 40	MBW 60	MBW 200	
Nominal voltage (Vdc) depends on jumpers		12/24		
Max. continuous current 5' (Amp)	40	60	200	
Peak current (Amp)	120	120	480	
Operating voltage range (Vdc)		8-32		
Consumption (mA)		< 3		
Alarm output delay	15 seconds			
Alarm output max. current (mA)	500			
Load disconnect delay	1	30 secondes		
Voltage level accuracy	0.2V	2%	0.1V	
Casework	Anodized aluminium, black			
Weight (gr)		580		
Dimensions HxDxL (mm)	80x60x40	80x60x40	145x92x85	
Battery protection		Against excessive dischar	ge	
Users protection	Against overv	roltages (16 / 32 Vdc)	Against overvoltages (15.5 / 31 Vdc)	
MOSFET switches	No sparks			
Norms	EN 50081-1 (emissio Automotive	on) EN 5008 <mark>2</mark> -1 (immunity) Directive 95/54/CE	EN 50081-1 (emission) Automotive Directive 95/54/CE	

MBR series



MBR – Microprocessor controlled battery separator

Model	MBR 12/24-100	MBR 12/24-160	MBR 12/24-500	
Nominal voltage (Vdc)	12/24	12/24	12/24	
Charge current max. (Amp)	100	160	500	
Connection threshold (Vdc) ± 2%	13.2/26.4	13.2/26.4	13.2/26.4	
Disconnection threshold (Vdc) ± 2%	12.8/25.6	12.8/25.6	11.8/23.6	
Battery banks	2			
Alternator start	•	•	•	
Start contact for batteries paralleling		•	•	
Micro switch for remote status indication			•	
Dimensions LxHxD (mm)	46x46x80	46x93x96	72x70x80	
Weight (gr)	110	300	417	
Consumption		< 5mA		
Protection of the auxiliary battery against overvoltage	16 / 32Vdc			
Connection on the battery side	N	M8		
Other connections		6.3 mm Faston		
Warranty		2 years		
orms EN 50081-1 (en		ssion) EN 50082-1 (immunity) Automotive Directive 95/54/CE		

5BM-02



SBM-02 - Battery monitor 12 and 24 Vdc (27-175 Vdc in option)

Model		SBM-02
Supply voltage ra	ange	9-35 Vdc
Consumption @ 12Vdc, without BL		9 mA
Consumption @ 24Vdc, without BL		7 mA
Input voltage range («Auxiliary» battery)		235 Vdc
Input voltage ran	ge («Main» battery)	035 Vdc
Input current range		-9999+9999 A
Battery capacity range		209990 Ah
Operating temperature range		-2050°C
Protection class		IP20 (Frontpanel IP65)
	Front panel	Ø 64 mm
Dimensions	Body diameter	Ø 52 mm
	Total depth	79 mm

38

Appendices

Jumper selectable voltage			
Disengage (V)	Engage (V)		
10	11.5		
10.5	12		
11	13		
11.5	13.8		
21.5	24.5		
22	25		
22.5	25.5		
23	26.5		

Standart equipment SBM-02
Potential free alarm contact
500A/50mV current shunt
Optional accessories
SBM-PS-02-Voltage pre-scaler 1:5 (adapting the SBM-02 to input voltage 27-175Vdc)
Connection kit, type SBM-CAB-20, including 20 m of twisted pair cable (3x2x0.5 mm2) and 2 fuseholders
Communication kit, type SBM-COM, including RS232 interface box, 1.8 m of 9p DSUB serial cable and a software
Communication kit, type SBM-COM-USB, including USB interface box, 1.8 m of USB cable and software.
Temperature kit, type SBM ;-TEMP-20, with 20 m cable
Shunt 1200 A/50 mV, type SH-1200-50



